



INSTALLATION



LOAD EQUALIZER 4807

PART #	INCLUDED
604710LE	1 Metric Load Equalizer
400839	3 Wire Connector
304807	1 Instruction Sheet

Please read and understand entire instructions before starting installation.

THANK YOU FOR CHOOSING KÜRYAKYN!

TOOLS SUGGESTED

Wire Stripper, Pliers

INSTALLATION GUIDELINES

- If you are not using a Kuryakyn Run-Turn-Brake controller, you will need to cut the white plug off the end of the wires.
- Depending on the model of your bike, this Load Equalizer should be installed where your main harness and the rear fender harness are connected. Typically located under the seat or side cover.
- One violet wire from the load equalizer should be connected to the right turn signal positive wire.
- One violet wire from the load equalizer should be connected to the left turn signal positive wire.
- The black wire from the load equalizer should be connected to a confirmed ground or the negative terminal on your battery.

WARNING! ALWAYS INSTALL THE LOAD EQUALIZER UPSTREAM OF ANY EXISTING AFTERMARKET MULTIFUNCTION CONTROL MODULES. DO NOT INSTALL A LOAD EQUALIZER BETWEEN A MODULE AND THE TURN SIGNALS AS THIS WILL OVERLOAD THE MODULE. OVERLOADING WILL DAMAGE THE MODULE AND CREATE A FIRE HAZARD!

WARNING! LOAD EQUALIZERS GENERATE HEAT WHEN IN USE. AVOID USING THE TURN SIGNALS FOR AN EXTENDED PERIOD OF TIME, OTHERWISE THE LOAD EQUALIZER WILL OVERHEAT. NEVER OPERATE THE FOUR-WAY FLASHERS UNLESS YOU FIRST REMOVE THE LOAD EQUALIZER. OVERHEATING WILL DAMAGE THE LOAD EQUALIZER, CAUSING LOSS OF TURN SIGNAL OPERATION AND CREATES A FIRE HAZARD!

Ride On!

CUSTOMER SERVICE

877.370.3604 (toll free)

INSTALLATION QUESTIONS

techsupport@kuryakyn.com
or call 715.247.2983

LIMITED WARRANTY

Kuryakyn warrants that any Kuryakyn products sold hereunder, shall be free of defects in materials and workmanship for a period of one (1) year from the date of purchase by the consumer excepting the following provisions:

- Kuryakyn shall have no obligation in the event the customer is unable to provide a receipt showing the date the customer purchased the product(s).
- The product must be properly installed, maintained and operated under normal conditions.
- Kuryakyn makes no warranty, expressed or implied, with respect to any gold plated products.
- Kuryakyn shall not be liable for any consequential and incidental damages, including labor and paint, resulting from failure of a Kuryakyn product, failure to deliver, delay in delivery, delivery in nonconforming condition, or for any breach of contract or duty between Kuryakyn and a customer.
- Kuryakyn products are often intended for use in specific applications. Kuryakyn makes no warranty if a Kuryakyn product is used in applications other than intended.
- Kuryakyn electrical products are warranted for one (1) year from the date of purchase by the consumer. Components of Kuryakyn products containing L.E.D.s will be warranted for defects in materials and workmanship for 3 years from the date of purchase.
- Kuryakyn makes no warranty of any kind in regard to other manufacturer's products distributed by Kuryakyn. Kuryakyn will pass on all warranties made by the manufacturer and where possible, will expedite the claim on behalf of the customer, but ultimately, responsibility for disposition of the warranty claim lies with the manufacturer.

ABOUT OUR CATALOG

You'll find all our innovations for H-D, GL and Metric Cruisers in our annual catalogs. Order online today—select the "CATALOGS" icon. Each Kuryakyn product comes with a Proof-of-Purchase good for a complimentary catalog. Details in packaging.

Be sure to ask your local dealer about other Kuryakyn products, the motorcycle parts and accessories designed for riders by riders.

©2005 Kuryakyn USA All Rights reserved.

